

XP/LINUX
Connectivity
Streams

any top-to-
bottom path
is a supported
configuration

<u>LINUX RedHat 6.0/6.1 Fibre Channel</u>			
Linux LVM		Standard	
		HA <u>Not Supported</u>	
<u>Servers</u> All listed with Linuxcare or RedHat as certified with an OS distribution specified above, running the applicable 2.2.x kernel. In addition, the server must be running with a driver/HBA specified below:			
<u>HBA's</u>			
	<u>PriNL</u> (boot)	<u>PubNL</u> (boot)	<u>DFA</u> (boot)
Qlogic QLA2100F	Y(n)	N(n)	N(n)
Qlogic QLA2200F	Y(n)	N(n)	N(n)
			Driver V2.23
			Driver V2.23
<i>PriNL=Private Loop; PubNL=Fabric Loop; DFA=Direct Fabric Attach (aka N-Port)</i>			
<u>Direct Connect</u>	<u>Hub</u>	<u>Switch</u>	
Yes: PriNL	No Plans	XP256 – No Plans XP-48/512 – No Plans	
See <u>CSU Heterogeneous SAN Configuration</u> for supported switch topologies			
XP256		XP512/48	
FW \geq 44.14.00 <u>Mode 00</u>		Direct Attach: FW \geq 11.22.00 <u>Mode 00</u> Switch: FW \geq 12.19.00	
XP Software			
Data Exchange XP.....NO	RAID Manager.....YES	Performance Manager XP.....YES	
Resource Manager.....YES	Command View XP.....YES	Performance Advisor XP.....YES	
Business Copy XP.....YES	Secure Manager XP.....YES	Auto LUN XP.....YES	
Continuous Access (CA) XP...YES	LUN Configuration Manager XP..YES	Continuous Track XP.....YES	
CA Ext'd XP.....YES	Cache LUN XP.....YES	Auto Path XP.....NO	
		Cluster Extension XP.....NO	

XP/LINUX
Connectivity
Streams

any top-to-
bottom path
is a supported
configuration

<u>LINUX RedHat 6.2 Fibre Channel</u>			
Linux LVM		Standard	HA <u>Not Supported</u>
<u>Servers</u> All listed with Linuxcare or RedHat as certified with an OS distribution specified above, running Kernel 2.2.14-5.0. In addition, the server must be running with a driver/HBA specified below:			
<u>HBA's</u>			
	<u>PriNL</u> (boot)	<u>PubNL</u> (boot)	<u>DFA</u> (boot)
Emulex LP8000	Y(n)	N(n)	Y(n)
Driver V4.10g			
<i>PriNL=Private Loop; PubNL=Fabric Loop; DFA=Direct Fabric Attach (aka N-Port)</i>			
<u>Direct Connect</u>	<u>Hub</u>	<u>Switch</u>	
Yes: PriNL	No Plans	XP-48/512 – Brocade 2400/2800, FW <= V2.1.9f, with Emulex LP8000 HBA	
See <u>CSU Heterogeneous SAN Configuration</u> for supported switch topologies			
XP256 Not Supported		XP512/48 FW \geq 01-12-19-00/00 <u>Mode 00</u>	
XP Software			
Data Exchange XP.....NO	RAID Manager.....YES	Performance Manager XP.....YES	
Resource Manager.....YES	Command View XP.....YES	Performance Advisor P.....YES	
Business Copy XP.....YES	Secure Manager XP.....YES	Auto LUN XP.....YES	
Continuous Access (CA) XP...YES	LUN Configuration Manager XP...YES	Continuous Track XP.....YES	
CA Ext'd XP.....YES	Cache LUN XP.....YES	Auto Path XP.....NO	
		Cluster Extension XP.....NO	